



Theta 60I

Theta 60I- Isolator

Product Code	TT60I-	X	XX	XX	X	XXXXXXXX
Combination	1 I/P 1 O/P 1/1	1				
	1 I/P 2 O/P 1/2	2				
	2 I/P 2 O/P 2/2	3				
Input Range	For Input Range refer Table No.A*		XX	XX		
Output Range	For Input Range refer Table No.B					
Power Supply	24-60V AC/DC				F	
	85-230V AC/DC			J		
Version	Standard					0000000

Table A For Input Range

Voltage & Current	Code	Voltage & Current	Code	Voltage & Current	Code	Voltage & Current	Code
-/+1mA	4	-/+75mV	0A	0-75mV	2H	0-20V	5L
-/+5mA	6	-/+10V	0M	0-200mV	2M	0-40V	5X
-/+10mA	8	-/+20V	0P	1-5V	3B		
-/+20mA	21	0-50mV	2C	2-10V	3C		
4-20mA	55	0-60mV	2E	0-10V	5H		



Table B for Output Range

Voltage & Current	Code	Voltage & Current	Code	Voltage & Current	Code	Voltage & Current	Code
0-1mA	26	-/+1mA	4	0-3V	5D	-/+10V	0M
0-2.5mA	28	-/+2.5mA	6	0-5V	5F	-/+15mA	9
0-5mA	29	-/+5mA	7	0-10V	5H	0-1V	5A
0-10mA	30	-/+10mA	8	2-10V	3C	1-5V	5B
0-20mA	32	-/+20mA	21	-/+5V	0K	0-12V	5J
4-20mA	55	4-20V	3D	0-2V 0.5 CL	5E	10-20mA	5G

Commonly Used codes for Theta 60I-

TT60-28C005555F000	Single I/P: 0-1000V DC; Dual O/P: 4-20mA DC; Aux: 24-60VACDC
TT60-28C005555J000	Single I/P: 0-1000V DC; Dual O/P: 4-20mA DC; Aux: 85-230VACDC
TT60-35H325555F000	Dual I/P: 0-10V DC; Dual O/P: 0-20mA DC, 4-20mA DC; Aux: 24-60VACDC
TT60-35H325555J000	Dual I/P: 0-10V DC, Dual O/P: 0-20mA DC, 4-20mA DC; Aux: 85-230VACDC
TT60-3325H5555F000	Dual I/P: 0-20mA DC; Dual O/P: 0-10V DC, 4-20mA DC; Aux: 24-60VACDC
TT60-3325H5555J000	Dual I/P: 0-20mA DC; Dual O/P: 0-10V DC, 4-20mA DC; Aux: 85-230VACDC
TT60-3325H5555F000	I/P1: 0-10V DC; I/P2: 0-20mA DC; Dual Output: 4-20mA DC; Aux: 24-60VACDC
TT60-3325H5555J000	I/P1: 0-10V DC; I/P2: 0-20mA DC; Dual Output: 4-20mA DC; Aux: 85-230VACDC