



Technical Data Sheet

VA40

*Auto Range Multimeter
with USB/LAN wire Test*



Product Features

Max. Display	5999
Auto/Manual Range	√
NCV Function	√
RMS Measurement	√
Max measurement	√
Relative measurement	√
Data hold	√
Back light	√
Diode test	√
Continuity test	√
LAN wire test	-
Phone test	-
Cable track	-
USB port connect to PC	-
Low power indication	√
Auto power off	√
Low battery detect	√
Power	Battery 6F22 (9V)X1
Size	190x90x40mm (7.48 x 3.54 x 1.57 inch)
Weight	~500g (including battery) (17.63 Ounces)

Product Specifications

DC Voltage	600mV±0.5%,6/60/600V±0.8%,1000V±1.0%
AC Voltage	600mV/6V/60V/600V±1.0%,1000V±1.5%
DC Current	600μA/6000μA/60mA/600mA/6A/10A±1.5%
AC Current	600μA/6000μA/60mA/600mA±1.5%,6A/10A±3%
Resistance	600Ω/6KΩ/60KΩ/600KΩ/6MΩ±0.5%,60Ω±1.5%
Capacitance	60nF±3%,600nF/6μF/60μF/600μF/6mF±5% (60mF)
Logic Frequency	10 Hz ~ 1MHz ±(0.1%+3)
Linear Frequency	6 Hz ~ 10KHz ±(0.05%+8)
Frequency	10 Hz ~ 1MHz ±(0.1%+3)
Temperature	-55°C~0°C ±5.0% (-67°F ~32°F), 0°C~1000°C±2.0% (32°F ~1832°F)



sifam tinsley
PRECISION INSTRUMENTATION

Sifam Tinsley Instrumentation Inc.
2105 Barrett Park Drive, Unit 105
Kennesaw, GA 30144 (USA)
E-mail Id : psk@sifamtinsley.com
Web : www.sifamtinsley.com
Contact No. : +1 678 881 0008 / 800 879 6171